

WARNING

Always handle the batteries with care and use them only as directed. Battery may explode if mistreated. Do not recharge, disassemble or dispose of in fire.

And also improper use may result in cracking or leakage, which could result in fire, injury and/or pollution of the surrounding environment.

- Be sure to use only the batteries specified. Do not use batteries of different types at the same time. Do not mix a new battery with used one.

- Make sure the plus and minus terminals are correctly aligned when loading a battery.

If the battery is placed in the battery holder upside-down, it may be hard to remove.

- Keep a battery away from children and pets. If swallowed consult a physician immediately for emergency treatment.

- Do not short circuit or solder a battery.

- Do not allow a battery in a fire or water. Keep batteries in a dark, cool and dry place.

- If you observe a leakage of a battery, wipe out the flower and then replace a battery. If the liquid adheres to your body or clothes, rinse well with water immediately.

- Obey the local laws on disposing the battery.

Replacing Internal Clock Battery




Consumption of the battery makes the clock not to work correctly. When the clock is wrong or it has stopped, please replace the battery according to the following procedures.

Replacing the clock batteries

The projector has a lithium Hitachi Maxell battery on the bottom that is used to power the clock used for networking applications.

Visit our website for complete details on using the networking functionality.

1. Turn off the projector and unplug the power cable.
2. Wait 45 minutes to allow the projector to cool thoroughly.
3. Turn the projector upside down and use a coin to turn the battery cover to the "Open" position.
4. Remove the battery and dispose of in an environmentally proper manner.
5. Install a new battery with the "+" side facing up.
6. Press the battery into place, then replace the battery cover.



NOTE

- The clock time will need to be reset in the web browser application after replacing the battery.